



# RCA-6D6

## TRIPLE-GRID SUPER-CONTROL AMPLIFIER



The 6D6 is a triple-grid super-control amplifier tube recommended for service in the radio-frequency and intermediate-frequency stages of radio receivers designed for its character-

istics. The ability of this tube to handle the usual signal voltages without cross-modulation and modulation-distortion makes it adaptable to the r-f and i-f stages of receivers employing automatic volume control. The 6D6 is constructed with an internal shield connected to the cathode within the tube.

### CHARACTERISTICS

HEATER VOLTAGE (A. C. or D. C.)	6.3	Volts
HEATER CURRENT	0.3	Ampere
PLATE VOLTAGE	100	250 max. Volts
SCREEN VOLTAGE	100	100 max. Volts
GRID VOLTAGE (Minimum)	-3	-3 Volts
SUPPRESSOR	Connected to cathode at socket	
PLATE CURRENT	8	8.2 Milliampere
SCREEN CURRENT	2.2	2.0 Milliampere
PLATE RESISTANCE	0.25	0.8 Megohm
AMPLIFICATION FACTOR	375	1280
TRANSCONDUCTANCE	1500	1600 Micromhos
TRANSCONDUCTANCE (At -50 volts bias)	2	2 Micromhos
GRID-PLATE CAPACITANCE (With shield-can)	0.007 max.	$\mu\mu\text{f}$
INPUT CAPACITANCE	4.7	$\mu\mu\text{f}$
OUTPUT CAPACITANCE	6.5	$\mu\mu\text{f}$
BULB		ST-12
CAP		Small Metal
BASE		Small 6-Pin

### INSTALLATION AND APPLICATION

The base pins of the 6D6 fit the standard six-contact socket which may be installed to hold the tube in any position.

For heater operation and cathode connection, refer to INSTALLATION for type 6A8.

For control-grid bias, screen voltage, and suppressor connection, refer to INSTALLATION on type 6K7. Shielding requirements are similar to those for type 6C6.

Refer to APPLICATION on type 6K7. A plate family of curves is given under type 58.



**page**

1  
2

**6D6  
sheet**

72  
FP

**date**

1937  
1999.10.10