

### LF voltage amplification

Socket type: Noval

Cathode type: oxide, indirect heating

Envelope: glass, miniature

Mass: 15 g

Filament voltage: 6,3 V

Filament current: 0,315 - 0,365 A

Anode voltage: 250 V

Anode current: 14 - 32 mA

Anode power: 1 W

Grid1 voltage: -1,5 V

Steepness: 1,6 - 2,65 mA/V

Reverse grid current: 0,05  $\mu$ A

Microphonic noise: 100 mV

Gain: 85 - 115

