

35W4



35W4

HALF-WAVE VACUUM RECTIFIER

Typical Operation Without Panel Lamp in Conventional
Half-Wave Circuit with Capacitor-Input Filter:

AC Plate-Supply Voltage (RMS).	117	volts
Filter-Input Capacitor	40	μ f
Min. Total Effective Plate-Supply Imped.	15	ohms
DC Output Current.	100	ma
DC Output Voltage at Input to Filter (Approx.):		
→ At half-load current (50 ma.)	135	volts
At full-load current (100 ma.)	120	volts
Voltage Regulation (Approx.):		
→ Half-load to full-load current	15	volts


Maximum Circuit Values:

Panel-Lamp Shunting Resistor:*

For dc output current of	70 ma.	800 max.	ohms
	80 ma.	400 max.	ohms
	90 ma.	250 max.	ohms

*Required when dc output current is greater than 60 ma.

HALF-WAVE CIRCUIT
with No.40 or No.47 Panel Lamp



DROP ACROSS R AND ALL HEATERS (WITH
PANEL LAMP) SHOULD EQUAL 117 VOLTS AT
0.15 AMPERE. R_s = SHUNTING RESISTOR
REQUIRED WHEN DC OUTPUT CURRENT
EXCEEDS 60 MILLIAMPERES

92CS-6626

Devices and arrangements shown or described herein may
use patents of RCA or others. Information contained
herein is furnished without responsibility by RCA for
its use and without prejudice to RCA's patent rights.

→ Indicates a change.

SEPT. 1, 1950


TUBE DEPARTMENT
RADIO CORPORATION OF AMERICA, HARRISON, NEW JERSEY

DATA



35W4

35W4 OPERATION CHARACTERISTICS HALF-WAVE RECTIFIER



MAY 19, 1950

TUBE DEPARTMENT
RADIO CORPORATION OF AMERICA, HARRISON, NEW JERSEY


92CM-6615R1

35W4



35W4

AVERAGE PLATE CHARACTERISTIC



92CM-6305TV

SEPT. 1, 1950

TUBE DEPARTMENT
RADIO CORPORATION OF AMERICA, HARRISON, NEW JERSEY

CE-6305TV