

Heathkit Cross Reference

Updated 11/12/02

Heath P/N	Generic P/N	Alternate 1	Alternate 2	Description
Signal Diode				
56-4	HD2257			Hughes Crystal Diode
56-5	HD6226			Hughes Crystal Diode
56-6	1N710	1N754		6.8 V Zener
56-7	1N2326			1.0 V 100mA Germanium V-Ref
56-8	ED-5			Erie Crystal Diode
56-9	1N294			Crystal Diode
56-10	G247			47pF Varactor
56-11	1N60A			Crystal Diode
56-12	1N2940			Crystal Diode
56-13	1N5943A	1N5370A		56 V Zener
56-16	1N751A	1N5231B	1N4733A	5.1 V Zener
56-17	STD633			Tunnel Diode
56-19	1N757A	VR9.1	1N5239B	9.1 V Zener
56-20	1N295	1N295S	1N60H	40V 35mA Germanium
56-24	1N458			150 PIV 100 mA Switching
56-25	1N4166A	1N4744		15V Zener
56-26	1N191			90 PIV 5 mA Germanium
56-27	S160			1500V 12A DO-4
56-29	VR110			110V Zener
56-31	PS18775			6.8 V Zener
56-32	VR13.5			13.5 V Zener
56-33	1N3754			100 PIV 0.13A Switching
56-35	1N4951			Dual Diode (Common Cathode)
56-36	VR16.1			16.1 V Zener
56-44	1N4653			4.7 V Zener
56-45	VR20			20 V Zener
56-46	1N4739A	1N5239B		9.1 V Zener
56-47	MZ1000-23			27 V Zener
56-48	BZT110A	1N3814	1N5379B	110 V Zener 15 mA
56-49	MV1638			30-36pF Varactor Diode
56-50	DO-7	5D20		2000 PIV 5mA DO-7
56-54	VRS-5A			5V Zener
56-55	VR36A			36 V Zener
56-56	1N4149	1N4148		100 PIV 10mA Switching
56-57	1N716A			12 V Zener
56-58	1N709A			6.2 V Zener
56-59	1N750A	1N5230B	1N4732A	4.7 V Zener

56-61	STB620			Stabistor (IG-1271)
56-63	MZ500-10			5.6 V Zener
56-64	MZ1000-24			30 V Zener
56-66	VR43	1N3035		43 V Zener
56-67	VR10A			10 V Zener
56-68	ZVR-68	1N5945A	1N5373A	68 V Zener
56-71	1N825A			6.2V Temp Comp Zener Diode
56-72	1N4755A			6 V Voltage Reference Diode
56-73	MZ2360			0.65 Forward Voltage Ref
56-74	MZ2362			2.00 Forward Voltage Ref
56-75	1N5338B			5.1 V Zener
56-76	1N972B			30 V Zener
56-77	FV1010			
56-78	FH6259			
56-79	R4507-5			
56-82	1N3996A			5.1V Zener Diode 10W Stud-Mtg
56-84	1N4148			100 PIV 10mA Switching
56-85	SZ5.0			5.0 V Zener
56-86	FD777			15 PIV 50mA RF
56-87	FH1100	1N5390		5 PIV "Hot Carrier" 890MHz
56-89	GD510			25 PIV 100mA Germanium
56-90	1N4742A			12 V Zener
56-91	1N823A			6.2 V Zener
56-93	FD333			125 V 150mA RF
56-94	Selected Zener			12.8 V @ 12 mA
56-97	VR7.5	1N3017		7.5 V Zener
56-99	1N5223B			2.7 V Zener
56-602	Unspecified			10 V PIV 200mA Germanium
56-604	1N4752A			33 V Zener
56-605	1N4746A			18 V Zener
56-606	1N5353B			16 V Zener
56-607	1N82AG			Silicon diode UHF Mixer
56-608	Unspecified			9.1 V Zener
56-612	1N5229B			4.3 V Zener
56-613	MV2110			35-43pF Varactor Diode
56-616	1N5232B			5.6 V Zener
56-617	1N5277B			160 V Zener
56-619	1N4733A			5.1 V Zener
56-620	1N4744			15 V Zener
56-621	1N4738A			8.2 V Zener
56-626	Selected Zener			56 V Zener 8mA

56-627	1N4741			11 V Zener
56-628	BY206			600PIV 1A Fast Recovery Diode
56-629	BZX83C3V			3V Zener
56-630	1N4748A	1N5933A		22 V Zener
56-634	2EZ82D5	1N5947A	1N5375A	82 V Zener
56-636	5082-2811	HP-5082		15V 20mA Schottky Diode
56-637	PS18775			6.8 V Zener
56-640	MV2110			35-43pF Varactor Diode
56-642	MV2107			22 pF Varactor Diode (at 4.0V)
56-646	BA-244			35 PIV 100A DO-35
56-648	MV109			26-32pF Varactor Diode
56-652	1N4448			75V 0.45A High Speed Switching
56-653	Selected Zener			91 V Zener
56-655	1N6263	SD101A		60 PIV 15mA Schottky
56-659	1N5998B			Selected Zener 8.2 V
56-669	1N5524D			5.6 V Zener
56-674	MV209			26-32pF Varactor Diode
56-675	MPN3404			20 PIV 10 mA Switching Diode
56-695	LM385Z-2.5			2.5V Zener Micro-Power TO-92
56-876	MBD201			K Band UHF/Micro TO-92

Rectifier Diode

57-1				Selenium Rectifier 250 PIV
57-2				65 mA Half Wave Sel Rectifier
57-6				Selenium Rectifier 450 PIV
57-7				Dual Half Wave Sel Rectifier
57-11	CX2C2D	Bradley CS2C2D437		Selenium Rectifier
57-12				Bridge Rectifier 150 PIV 150mA
57-13	Sarkes Model 50			Selenium Rectifier 200 PIV
57-15				100 mA 130 PIV
57-16				100 mA 175 PIV
57-17				500 mA
57-18				20 Amp
57-20				500 mA
57-21	Unspecified			150 mA
57-22				10 mA 130 PIV Selenium Recti
57-23				200 mA 200 PIV
57-25				65 mA 130 PIV
57-27	1N2071	1N4005		600 PIV 1A Rectifier
57-29	U-131			Silicon Diode (Selected)
57-34	1N3491			400V 25A Rectifier
57-40				SCR

57-42	3A1	1N5403	300 PIV 3A Rectifier
57-46	DRS102		600V 1A DO-41
57-50	TIC44	TI1001	30V 800mA SCR TO-92
57-51	TIC47		200V 800mA SCR TO-92
57-52	DO-7	5D20	2000 PIV 5mA DO-7
57-56	SCM-30		3000 PIV 5mA DO-7
57-57	GRS7PH280BAB		
57-58	40642		
57-59	40643		
57-60	40644		
57-64	DRS-110	1N4007	1000V 1A DO-41
57-65	1N4002		100 PIV 1A Rectifier
57-67	10A20		Full Wave Bridge
57-71	1N825A		6.2V Temp Comp Zener Diode
57-84	45412	1N5759A	DIAC
57-85	40668		TRIAC
57-86	SPS135	NL576A	SCR
57-88	MDA990-2		100V 30A FW Bridge Rectifier
57-89	MR1122		200 PIV 12A DO-203
57-91	41018		
57-94	41021		
57-95			Diode Bridge
57-99	2N6151		Triac
57-602	S3900MF		
57-603	S3901M		
57-604	SR711A		Dual Diode Common Anode TO-3
57-607	1N5817		20 PIV 1A Schottky Rectifier
57-608	1N5831		25 A Schottky rectifier (Stud)
57-609	1N5393		200 PIV 1.5 A
57-610	FM-50		6000 PIV 3 mA
57-612	T2302F	H103SG	Triac
57-614	MR-508		800 PIV 3 A
57-615	MBS4991		Bilateral Switch
57-621	MBS4992		Diac
57-624	2N5061		60V 500mA SCR TO-92

Assemblies

100-1727	Temp Sensor	New Stock Available	Temp Sensor for ID-4001/5001
100-1728	Temp Sensor	New Stock Available	Temp Sensor for ID-4001/5001

Solid-State Tube

150-57	TR-1002			Solid-State "6AL5" Replcmnt
150-58	TR-1119			Solid-State "12AU7" Replcmnt

Display

411-89	FND500			7-Seg Display Common Cathode
411-264	NL905S	B-5859S	NL1220	"Nixie" Display tube
411-281	SP-733			Sperry/Beckman 3 Digit Display
411-284				"Nixie" Display tube
411-286	SP-352			Sperry/Beckman 2 Digit Display
411-290	SP-353			Sperry/Beckman 3 Digit Display
411-295	SP-352			Sperry/Beckman 2 Digit Display
411-807	TIL308			BCD Display Driver LED
411-819	FND500			7-Seg Display Common Cathode
411-823	FND507			7-Seg Display Common Anode
411-825	FND367	FND5141		7-Seg Display Common Cathode
411-831	TIL-312			7-Seg Display
411-835	5082-7760			7-Seg Display Common Cathode
411-836	Futaba 4BT-04			LCD Clock Display (4 Digit)
411-843	Beckman 739-02050	Hamlin 3933-363-159	AND FE0203	LCD Display (3 1/2 Digit)
411-859	DS108	5082-7756		+ .1. Display Common Cathode
411-860	5082-7760			7-Seg Display Common Cathode
411-875	MAN-			7-Sec Display Common Anode
411-885	FND500			7-Seg Display Common Cathode

Display

412-66				Lamp IG-18 /IG-5218
412-79	TIL209			
412-616	FLV117			LED T 1 3/4 Red
412-621	Custom Lamp			5V 120 mA 20,000 Hr T-1 Wedge
412-633	5082-4484			LED

412-634	5082-4670	HLMP-0501	LED
412-635	TIL32	QEC113	IR LED T1
412-640	LST5053		LED
412-644	LST71		LED (Red/Green)
412-646	151B		LED
412-647	251B		LED
412-648	SL247504		4 Digit Display
412-654	HLMP-1002		LED
412-657	HLMP-504		

Transistor

417-1	2N109			PNP 35V 150 mA TO-40 (Ger)
417-2	2N252			PNP 20V 10mA TO-22 (Ger)
417-3	2N253			NPN 12V 5mA TO-22 (Ger)
417-4	2N254			NPN 20V 5mA TO-22 (Ger)
417-5	2N238			PNP 20V 10mA TO-22 (Ger)
417-6	2N185			PNP 20V 100mA TO-22 (Ger)
417-7	2N308			PNP 20V 5mA TO-22 (Ger)
417-8	2N309			PNP 20V 5mA TO-22 (Ger)
417-11	2N1108			PNP 16V 5 mA (Ger)
417-12	2N1110			PNP 16V 5 mA (Ger)
417-13	2N1111			PNP 16V 5 mA (Ger)
417-14	2N373			PNP 15V 100mA (Ger)
417-15	2N374			PNP 15V Hi Speed (Ger)
417-16	2N544			PNP 35V 10mA TO-7 (Ger)
417-17	R-250			
417-18	2N408			PNP 20V 70mA TO-1 (Ger)
417-19	R-270			
417-20	2N2553	R265A	2N1039-1	PNP 40V 3A Str-10 (Ger)
417-21	2N1274			PNP 25V 50mA TO-5 (Ger)
417-22	2N1107			PNP 16V 5 mA (Ger)
417-23	2N1109			PNP 16V 5 mA (Ger)
417-24	R-251			
417-25	2N1396			PNP 40V 2mA TO-33 (Ger)
417-26	2N1225			PNP 40V 10mA TO-12 (Ger)
417-27	2N409			PNP 10V 15mA TO-40 (Ger)

417-28	2N407		PNP 20V 35mA (Ger)
417-29	2N1147		PNP 100V 5mA TO-41 (Ger)
417-30	CDT1337		
417-31	600RF		
417-32	2N383		PNP 50V 400mA TO-5 (Ger)
417-33	R-424		
417-34	600RFA		
417-35	TS603		PNP 32V 1A TO-3 (Ger)
417-36	R-425		
417-37	2N1726		PNP 20V 50mA TO-9 (Ger)
417-38	2N1727		PNP 20V 50mA TO-9 (Ger)
417-39	2N1108 Selected		PNP 16V 5 mA (Ger)
417-40	T-6025		
417-41	T-6026		
417-42	CQT701A	2N1548	PNP 60V 5A TO-3 (Ger)
417-43	2N398A		PNP 50V 150mA TO-5 (Ger)
417-44	2N2147		PNP 75V 5A TO-3 (Ger)
417-46	34022		
417-47	T-1577		
417-50	TI363		PNP 20V 10mA 700MHz (Ger)
417-51	2N185		PNP 20V 100mA TO-22 (Ger)
417-53	TI364		PNP 20V 10mA 900MHz (Ger)
417-54	T2384		
417-56	T2379		
417-57	2N1747		PNP RF-Amp (Ger)
417-59	2N2217		NPN 60V 800mA TO-5
417-62	34715		
417-66	34942		
417-67	2N2712		NPN 18V 100mA TO-98
417-68	35070		
417-70	2N2671		PNP 25V 10mA TO-12 (Ger)
417-71	2N2654		PNP 25V 10mA TO-12 (Ger)
417-72	2N2495		PNP 40V 10mA TO-12 (Ger)
417-73	2N1525		PNP 20V 10mA TO-72 (Ger)
417-74	2N1526		PNP 24V 10mA TO-1 (Ger)
417-77	2N2712 Selected		NPN 18V 100mA TO-98
417-78	2N1524		PNP 24V 10mA TO-1 (Ger)
417-82	B846		
417-83	L842	2N3854	NPN 30V 50mA TO-92
417-84	E843		NPN 30V 50mA TO-92
417-85	E844		NPN 30V 50mA TO-92

417-86	A845	2N2924	NPN 30V 500mA TO-92
417-89	7409		25 V Dual Gate N-ChN MOSFET
417-90	40050		PNP 40V 5A TO-3 (Ger)
417-91	2N5232A		NPN 50V 100mA 0.3W TO-92
417-93	2N3646		NPN 15V 200mA TO-106 (200MHz)
417-94	2N3416		NPN 50V 500mA TO-92
417-96	4JX5E670		Unijunction Transistor
417-99	2N2148		NPN 40V 10mA TO-18 (300MHz)
417-100	2N3053		NPN 60V 700mA 1W TO-39
417-101	TA2577A		NPN 100V 15A TO-3
417-103	2N1303		PNP 30V 300mA TO-5 (Ger)
417-104	37436		
417-105	SE5023		NPN 45V 50mA 600MHz
417-106	SE5024		NPN 45V 50mA 600MHz
417-107	SE5025		NPN 45V 50mA 600MHz
417-108	2N3692		NPN 20V 200mA TO-92 (200MHz)
417-109	2N3566		NPN 30V 200mA TO-105 (40MHz)
417-110	S2090		
417-112	2N3731		PNP 320V 10A TO-3 (Ger)
417-114	2N3567		NPN 40V 500mA TO-105 (60MHz)
417-115	2N3923		NPN 300V 10mA TO-39
417-116	S2091		PNP 80V 1A
417-118	2N3393		NPN 25V 0.5A .625W TO-92
417-119	CA3013		Transistor Array (TV-Sound)
417-120	Unspecified		PNP Germanium Power Transistor
417-121	2N2430		NPN 32V 300mA TO-1 (Ger)
417-122	2N2431		PNP 32V 300mA TO-1 (Ger)
417-123	CA3012		Wide Band IF Amp (Linear IC)
417-125	2N3563		NPN 30V 200mA TO-106 (300MHz)

417-126	2N3565		NPN 25V 200mA TO-106
417-133	40245		NPN 45V 300mA TO-72 (UHF)
417-134	MPS6520		NPN 25V 100mA TO-92 (120MHz)
417-135	2N3859A		NPN 30V 100mA TO-98 (100MHz)
417-136	40408		NPN 90V 700mA TO-5 (100MHz)
417-137	40409		NPN 90V 700mA TO-5 (100MHz)
417-138	40410		PNP 90V 700mA TO-5 (100MHz)
417-139	40411		NPN 90V 30A 150W TO-3
417-140	2N4304		JFET 30V 15mA TO-106 (N-Ch)
417-141	2N2869	2N301	PNP 50V 10A TO-3 30W (Ger)
417-142	DTG-600		PNP 50V 15A 60W TO-204 (Ger)
417-144	MJE521		NPN 40V 4A 40W TO-127
417-145	MJE371		PNP 40V 4A 40W TO-126
417-150	2N1274		PNP 25V 50mA TO-5 (Ger)
417-154	2N2369	2N2369A	NPN 40V 200mA .36W TO-18
417-155	2N3641		NPN 60V 500mA
417-162	2N3055	MHT9210	NPN 100V 15A 115W TO-3
417-164	16G2349		
417-167	UC734		JFET 30V 10mA TO-72 (N-Ch)
417-168	TIS37		PNP 80V 1A TO-92
417-169	MPF105	2N5459	JFET 25V 16mA TO-92 (N-Ch)
417-170	MPS6522		PNP 25V 100mA TO-92
417-171	2N3694		NPN 45V 30mA TO-106 (200MHz)
417-172	MPS6521		NPN 25V 100mA TO-92 (120MHz)
417-173	ETS083	2N2509	NPN 80V 200mA TO-18
417-174	PET9001		
417-175	2N5294	TA2911	NPN 75V 4A TO-220 (800kHz)

417-178	40389			NPN 40V 700mA TO-5 (100MHz)
417-180	40346			NPN 175V 1A TO-5
417-181	40391			PNP 60V 1A TO-5 w/HS
417-183	2N4894			
417-186	2N3958			JFET 50V 5 mA TO-92
417-190	40481			NPN 45V 50mA TO-72
417-191	TD101			NPN 60V 500mA 200MHz
417-195	MJE340			NPN 300V 500mA 20W TO-225
417-200	X29A826			PNP 80V 1A TO-92
417-201	X29A829	D29A4	2N3906	PNP 80V 1A TO-92
417-203	TA7311			NPN 70V 10A TO-127
417-205	2N3866			NPN 55V 400mA TO-39 (UHF)
417-206	40673	40675	3N201	Dual Gate MOS-FET20V 50mA TO72
417-207	40468			MOS-FET 20V 20mA TO-104 (N-Ch)
417-213	2N5249A			NPN 50V 100mA 0.3W TO-92
417-215	2N3055			NPN 100V 15A 115W TO-3
417-218	TZ1160			
417-219	SS9328			PNP 180V 1A TO-202
417-220	SS9327	MM3006		NPN 180V 1A TO-202
417-221	TZ582			PNP 60V .5A TO-92
417-222	2N5308			NPN Dar 40V 300mA 0.4W TO-92
417-223	40673	40675	3N201	Dual Gate MOS-FET20V 50mA TO72
417-224	MPSU05			NPN 60V 2A Mot "Uni-Watt"
417-225	MPSU55			PNP 60V 2A Mot "Uni-Watt"
417-228	SE5055			NPN 20V 15mA TO-72
417-229	MPS6544			NPN 60V 100mA TO-92
417-	40646			

230				
417-232	SE7056	FT123		NPN 300V 30mA TO-39
417-233	2N3643			NPN 30V 500mA TO-105
417-234	2N3638A			PNP 25V 500mA TO-92 (100MHz)
417-235	2N4121			PNP 40V 200mA TO-106 (UHF)
417-237	SE6020			NPN 60V 1A TO-105
417-238	40648			
417-239	TA7420	MJ3029		NPN 800V 10A TO-3 Horiz Output
417-240	40673	40675	3N201	Dual Gate MOS-FET 20V 50mA TO72
417-241	EL131			JFET 25V 10mA (N-Ch)
417-242	Unspecified			*Select Zener (Transistor)
417-244	2N5089			NPN 25V 50mA 0.3W TO-92
417-245	D40N1	MJE340		NPN 250V 100mA TO-202 (90MHz)
417-246	TIS74			JFET 30V 100mA TO-92
417-251	SFC2912	UC734		JFET
417-254	MJ802			NPN 90V 30A 200W TO-3
417-256	2N4360	2N5033		FET
417-258	TIS87			NPN 45V 50mA TO-92 (UHF)
417-260	2N4258A			PNP 12V 50mA TO-222 (UHF)
417-261	TD401			PNP 40V .5A
417-263	SJE607			PNP 80V 4A TO-126
417-264	SJE608			NPN 80V 4A TO-126
417-265	2N5033			JFET 20V 3.5mA TO-18 (P-Ch)
417-267	MPS6560			NPN 25V 500mA TO-92
417-268	MPS6562			PNP 80V 1A TO-92
417-269	SGC5282			
417-270	SGC5283			
417-	D40C1			NPN Dar 30V 500mA TO-202

272				
417-274	40673	40675	3N201	Dual Gate MOS-FET20V 50mA TO72
417-275	MPS6522			PNP 25V 100mA TO-92
417-278	Unspecified			PNP Germanium Power (Selected)
417-279	FM1108			Dual FET
417-282	MJ2841			NPN 80V 10A 150W TO-3
417-283	SMO7275			NPN 40V 800mA 300MHz
417-284	SM62186			PNP 15V 200mA 850MHz
417-286	2N4347			NPN 250V 15A TO-3
417-288	2N4416	PN4416		JFET 30V 30mA TO-72 (N-Ch)
417-289	2N6109			PNP 50V 7A TO-220 (10MHz)
417-290	MRF502			NPN 35V 50mA TO-72 (UHF)
417-291	2N5458			JFET 25V 0.25A TO-92 (N-Ch)
417-292	2N5771			PNP 30V 0.05A 0.63W TO-92
417-293	2N5770			NPN 30V 0.05A 0.63W TO-92
417-294	MPSA42			NPN 300V 500mA TO-92 (50MHz)
417-295	MPSL51	2N5400	2N5401	PNP 100V 600mA TO-92
417-296	TA311			
417-298	TIP41B			NPN 80V 300mA TO-220
417-299	2N5591	CTC B25-12		NPN 36V 4.0A 200MHz T72
417-801	MPSA20			NPN 40V 100mA TO-92 (125MHz)
417-802	E304	MPF102 (Selected)		JFET 30V 15mA (N-Ch)
417-803	2N6081	2N5590		NPN 18V 2.5A 30W Stx-8
417-804	2N6080	2N5589		NPN 18V 1A 12W Stx-8
417-805	2N4889			PNP 150V 100mA TO-222 (160MHz)
417-806	TIS75			JFET 30V 10mA TO-92 (N-Ch)
417-807	2N6175			NPN 250V 1A TO-126 (20MHz)

417-808	2N3702			PNP 25V 0.5A .625WTO-92
417-809	2N3704			NPN 50V 800mA TO-92
417-811	MPSL01	2N5550	2N5551	NPN 120V 150mA TO-92
417-812	E421			Dual JFET 50V 50mA (N-Ch)
417-813	2N4959			PNP 30V 200mA TO-72 (450MHz)
417-814	DTS409			NPN 400V 3.5A TO-3
417-818	MJE181			NPN 60V 3A 12W TO-225
417-819	MJE171			PNP 60V 3A 12W TO-225
417-820	2N4342			JFET 25V 12mA TO-222 (P-Ch)
417-821	MPSA06			NPN 80V 500mA TO-92 (100MHz)
417-822	MPSA56			PNP 80V 500mA TO-92 (50MHz)
417-823	MPU131			Uni-Junction 40V 200mA TO-92
417-828	E304 (Selected)	MPF102 (Selected)		JFET 30V 15mA (N-Ch) Idss=10
417-830	PT6619	CD3342		
417-831	2N6456	CD2664A	PT5767	NPN 25V 12A 75W (60MHz)
417-833	2N6306			NPN 250V 8A TO-3 (5MHz)
417-834	MPSU10			NPN 300V 500mA Mot "Uni-Watt"
417-836	MPSD51			PNP 200V 100mA TO-92
417-839	2N5179			NPN 20V 50mA TO-72 (UHF)
417-847	1B05			NPN 250V TO-3
417-849	TZ553			PNP 60V .5A TO-92
417-851	LPT1000			Photo Diode
417-852	TIP31B			NPN 40V 3A TO-220
417-853	SF83045			
417-854	SF50077	E304		JFET 30V 15mA (N-Ch)
417-856	MJE5979			NPN 100V 5A 75W TO-220
417-857	MJE5976			PNP 60V 10A 90W TO-127

417-858	P1087E	JFET 30V 5mA TO-92 (P-Ch)
417-863	MFE131	Dual Gate MOS-FET25V 30mA TO72
417-864	MPSA05	NPN 60V 500mA TO-92 (100MHz)
417-865	MPSA55	PNP 60V 500mA TO-92 (50MHz)
417-868	RCA29C	NPN 100V 3A TO-220
417-869	RCA30C	PNP 100V 3A TO-220
417-870	RCA1A16	PNP 100V 1A TO-39
417-872	TIP32	PNP 70V 7A TO-220
417-874	2N3906	PNP 40V 0.2A 310mW TO-92
417-875	2N3904	NPN 40V 0.2A 310mW TO-92
417-876	CA3046	Transistor Array Diff Amp (3)
417-877	CA3018A	Transistor Array Darlington
417-878	Selected FET	
417-879	2N3251	PNP 40V 200mA TO-18 (300MHz)
417-880	2N4427	NPN 40V 400mA TO-39 (UHF)
417-881	MPSA13	NPN Darl 30V 500mA TO-92
417-882	MPSA20 (Selected)	NPN 40V 100mA TO-92 (125MHz)
417-883	MPSU10 (Selected)	NPN 300V 500mA Mot "Uni-Watt"
417-884	Unspecified	Selected Transistor (Zener)
417-885	MPSA65	PNP Darl 30V 300mA TO-92
417-887	MPSH10	NPN 30V 40mA TO-92 (UHF)
417-892	MJ2941	NPN 80V 10A 150W TO-3
417-893	2N5109	NPN 35V 500mA TO-39 (UHF)
417-895	PIC625	
417-896	PIC600	
417-897	Selected FET	
417-	S2090 Selected	

900			
417-901	S2091 Selected		PNP 80V 1A
417-902	NPD5566N		JFET 40V 30mA N-Ch Dual 8-PDIP
417-903	40363		NPN 35V 7A TO-3
417-904	MPSU60		PNP 300V 500mA TO-92
417-905	2N3773		NPN 140V 16A TO-3 (200kHz)
417-906	2N6609		PNP 140V 16A 150W TO-3 200MHz
417-907	2N6274		PNP 100V 50mA TO-3
417-908	2N4117		JFET 40V 50mA TO-72 (N-Ch)
417-912	MRF237		NPN 18V 1A TO-39 (UHF)
417-914	F-317-B		NPN 140V 2A TO-220
417-915	F-417-B		PNP 140V 2A TO-220
417-917	MPSH81		PNP 20V 40mA TO-92 (UHF)
417-918	2N6387		NPN Dar 60V 10A TO-220 (20MHz)
417-919	TIL78	QSC114	Photo Transistor T1
417-920	2N4403		PNP 40V 600mA 0.3W TO-92
417-923	BU-500		NPN 1500V 6A TO-3
417-924	MJE172		PNP 100V 3A 12W TO-225
417-926	MPSU06		NPN 80V 2A Mot "Uni-Watt"
417-927	MPSA93		PNP 200V 500mA TO-92
417-928	2N6592		NPN 200V .5A TO-220 (70MHz)
417-931	PN4858		JFET 40V 50mA TO-92 (N-Ch)
417-932	MJE182		NPN 100V 3A 12W TO-225
417-934	2N5770 (Selected)		NPN 30V 0.05A 0.63W TO-92
417-937	MPS2369		NPN 40V 500mA TO-92 (UHF)
417-943	MJE15030		NPN 150V 8A TO-220
417-944	MJE15031		PNP 150V 8A TO-220
417-	MJ15024		NPN 250V 16A TO-3

945			
417-946	MJ15025		PNP 250V 16A TO-3
417-947	MDS21		NPN 300V 500mA TO-202
417-948	MDS60		PNP 300V 500mA TO-202
417-951	MRF247		NPN 35V 20A 6-Tab 175MHz
417-952	2N6081		NPN 18V 2.5A 30W Stx-8
417-953	TIP150		NPN 300V 7A TO-220
417-959	MD5000B		PNP 20V 50mA TO-99
417-962	MRF421		NPN 20V 20A 290W (UHF)
417-965	NSDU06		NPN 80V 2A "Uni-Watt 50MHz
417-975	CA3127		NPN Transistor Array Ind
417-999	VN10KM		JFET 60V .5A TO-92TAB

Linear IC

442-2	SN4985N	SN82809	
442-3	SN72710	LM710	Voltage Comparator
442-4	CA3035		RF Amp IC
442-5	CA3044VI		
442-9	MC1310P		MPX Decoder
442-10	uA746E		Dual Chroma Demodulator
442-11	CA3042		
442-18	MC1350P		Video IF Amp IC
442-19	75450N		Dual Peripheral Driver
442-20	uA703		Op Amp
442-21	MC1458		Dual 741C
442-22	N5741V		Op Amp
442-24	LM376		Adj Voltage Regulator (Pos)
442-25	LM310H		Op Amp Follower
442-28	MC1357P		IF Amp Quadrature Detector
442-30	uA309K		5 V Regulator (Pos)
442-33	MC1328		
442-34	87403		Four Channel Decoder Chip
442-35	uA308AHC		Precision Op Amp
442-36	LM311		Comparator
442-39	LM301A	LM101	Op Amp
442-41	uA739		Dual Audio Pre-Amp

442-46	MC1310	Stereo Decoder PLL
442-47	SG-2501	Dual Tracking +/- Regulator
442-48	MFC6030	Regulator IC
442-50	U760	High Speed Op Amp
442-53	NE555V	General Purpose Timer
442-54	uA7805	5 V Regulator (Pos)
442-55	MC1349P	FM / TV Sound IF
442-56	MC1330P	Video Sync Detector
442-57	MC1370P	Sync Detector Sound Demod
442-58	MC1371P	TV Chroma IF Amp
442-59	MC1364P	Automatic Fine Tuning Detector
442-60	MC7824	24 V Regulator (Pos)
442-62	MC1358P	TV Sound IF Detector
442-63	uA7815	15 V Regulator (Pos)
442-65	SG4501N	Dual Tracking +/- Regulator
442-66	LM308	Precision Op Amp
442-69	MC1312P	SQ Decoder (4-ch) SQ
442-71	LM3900	Quad Op Amp
442-73	75107	TriState Line Receiver
442-74	MD1344P	
442-75	LM311	Comparator
442-78	UHP481	
442-80	MC1398P	TV Color Processor
442-82	N5741	Op Amp
442-83	UHP480	
442-88	MC1314P	Audio Logic (4-ch) SQ
442-89	MC1315P	VCA (4-ch) SQ
442-92	CA3089	RCA FM IF IC
442-96	MC1496G	Balanced Mod/Demod IC
442-99	CD4016	CMOS Analog Switch
442-602	LM324N	Quad Op Amp Single Supply
442-603	78M05	5 V Regulator (Pos)
442-604	CD4007	CMOS Buffer
442-605	QSI5022	CD-4 Demodulator IC
442-609	78M20C	20 V Regulator (Pos)
442-610	TBA820	Audio Amplifier 2W
442-612	LM386N	1.5 W Audio Power Amp

442-613	MC7915			12 V Regulator (Neg)
442-615	uA739			Dual Audio Pre-Amp
442-616	LM2901	uA775	LM3302N	Quad Single Supply Comparitor
442-617	uA78MGT2C			Adj Voltage Regulator (Pos)
442-618	uA79MGT2C			Adj Voltage Regulator (Neg)
442-619	ICL8049			Anti-Log Op Amp
442-620	MC1391P			TV Horizontal Processor
442-621	78M24C			24 V Regulator (Pos)
442-622	MC1331P			
442-623	CA3130S			Op Amp
442-624	5322			Color Generator Chip
442-625	ULN2111			FM IF & Detector IC
442-626	78MGT4C			Adj Voltage Regulator (Pos)
442-627	78L05			5 V Regulator (Pos)
442-628	GPD401			Avantek RF Amplifier
442-629	GPD402			Avantek RF Amplifier
442-630	MC7905			5 V Regulator (Neg)
442-638	MK5086N-4			
442-639	LM308AN			Op Amp
442-640	CA3080			High Perf Op Amp
442-644	LM78L12			12 V Regulator (Pos)
442-646	MC79L12AC			12 V Regulator (Neg)
442-647	CD4046AE			CMOS PLL
442-648	LM310N			Op Amp Follower
442-649	SF7-0890			Avantek RF Amplifier
442-650	78H12			12 V Regulator (Pos)
442-651	78H05			5 V Regulator (Pos)

442-654	565			PLL
442-655	LM349			Quad Wide-band 741 Op Amp
442-658	HA1197			Signal Meter Drive (Hitachi)
442-663	CA3130-05		Heathkit P/N Error	Transistor Array
442-663	78M12CKC		Heathkit P/N Error	12 V Regulator (Pos)
442-664	79M12CKC			12 V Regulator (Neg)
442-665	79L05			5 V Regulator (Neg)
442-670	LF356N			Bi FET Op Amp
442-672	NE645B			Compander Amp
442-674	MC7812			12 V Regulator (Pos)
442-675	MC7912			12 V Regulator (Neg)
442-676	TDA2190			
442-678	7106			DVM Chip
442-679	TL061CP			Low Power JFET Op Amp
442-681	78L08			5 V Regulator (Pos)
442-685	uA78GKC			Adj Volt Reg (Pos) TO-3 (4pin)
442-687	78L10			10 V Regulator (Pos)
442-688	NE567N			DTMF Tone Decoder
442-691	78M08			8 V Regulator (Pos)
442-693	LM322N			Precision Timer
442-694	uA2240PC			Programmable Timer
442-695	78L15			15 V Regulator (Pos)
442-696	79L15			15 V Regulator (Neg)
442-698	SL952			Wide RF Amplifier (512 MHz)
442-699	1873	136PC	137PC15A212	Pressure Transducer (ID-4001)
442-700	LM3524	SG3524		Switching Regulator
442-				Pressure Transducer (ID-4001)

701			
442-703	LM350K		Adj Voltage Regulator (Pos)
442-706	NE5534		Single Low Noise Op Amp
442-707	LF353		Quad JFET Op Amp
442-708	LM317		Adj Voltage Regulator (Pos)
442-709	LM337		Adj Voltage Regulator (Neg)
442-710	XR2206		VCO IC
442-711	LM342		Prec Fahrenheit Temp Sensor
442-712	LM320		Fixed Voltage Regulator
442-715	CA3130		Op Amp
442-716	LM330T		5 V Regulator (Pos)
442-721	HA12412		FM Receiver Chip
442-722	uPC1173C		FM Stereo Decoder
442-723	TL489		Bar Graph Display
442-724	7107		DVM Chip
442-726	TL062CP		Dual JFET Op Amp
442-728	LM2904		Low Power Op Amp
442-733	LM358		Dual Op Amp
442-734	LM388N		1.5 W Audio Power Amp
442-740	LM556		Dual 555 Timer
442-741	XR2209		Precision Oscillator (Exar)
442-743	HA4741-5		Op Amp
442-744	CD4066BCN		Quad Bilateral Switch
442-748	ULN2280B		Audio Power Amp
442-751	LM1408N-8	DAC0808	A/D Converter
442-753	9402		V to F Converter
442-756	LF347	TL074	Quad JFET Op Amp
442-	LF411		J-FET Op Amp Low Offset

759			
442-760	5437		White Noise Generator
442-762	LM388N-1		1.5 W Audio Power Amp
442-763	LM388N-3		1.5 W Audio Power Amp
442-765	TL852CN		Polaroid Sonar Ranging Receiver
442-768	DAC1021		10-Bit (Mult) D/A Converter
442-769	ADC0820		8-Bit A/D Converter
442-771	LM361		High Speed Comparitor
442-774	CD4052		4 Chan Analog Mux
442-779	MF-10		Maxim Switched Cap Act Filter
442-780	2211		PLL IC
442-782	LF357		J-FET Op Amp
442-786	MPX100AP	MPX2100AP	Pressure Transducer (ID-5001)
442-787	LP2950C		Low Drop-out Voltage Regulator
442-789	RCA4192		
442-801	TLC555		CMOS Timer
442-840	NE566N		VCO Function Generator

Digital IC

443-1	7400N		Quad 2-input NAND
443-2	7420N		Dual 4-Input NAND
443-3	7430N		8-Input NAND
443-4	7472N		JK Flip-Flop
443-5	7473N		Dual JK Flip-Flop
443-6	7474N		Dual D Flip-Flop
443-7	7490N		Decade Counter
443-8	MC724P		Quad 2-Input NAND (RTL)
443-9	MC790P		Dual J-K FF (RTL)
443-10	MC723P		Single J-K FF (RTL)
443-12	7410N		Triple 3-Input NAND
443-13	7475N		4-Bit Bistable Latch
443-14	MC789P (Selected)		Hex Inverter
443-15	7450N		Dual 2-Wide 2-In And-OR-Invert

443-16	7476N		Dual JK Flip-Flop
443-17	74141A		BCD to Decimal Decoder
443-18	7404N		Hex Inverter
443-19	N8290A		Decade Counter
443-21	MC717P		
443-22	74121N		Monostable Non-Retrig
443-23	74122N		Retrig Monostable
443-25	74151N		8:1 Multiplexer
443-26	74S00		Quad 2-Input NAND
443-27	SN158093N	MC668P	Dual JK Flip-Flop
443-28	CuL995879		Decade Counter
443-29	CuL995979		4-Bit Buffer-Storage
443-30	CuL996079		"Nixie" Decoder Driver
443-31	MC726P		Single JK Flip-Flop (RTL)
443-32	MC790P		Dual JK Flip-Flop
443-34	7492N		4-bit Counter
443-35	7441N		BCD to Decimal Decoder 70V
443-36	7447N		BCD to 7-Segment Decoder
443-37	74100N		8-Bit Bi-Stable Latch
443-38	MC1023P		Dual NOR/OR Gate
443-39	MC1034		Single D Flip-Flop
443-40	MC1013P		Single JK Flip-Flop
443-41	MC1027P		
443-42	74S112N		Dual JK Flip-Flop
443-43	74H102N		JK Flip-Flop
443-44	7413N		Dual 4-Input NAND (Schm Trig)
443-45	7408N		Quad 2-Input AND
443-46	7402N		Quad 2-Input NOR
443-53	7442N		4:10 Line Decoder
443-54	7403N		Quad 2-input NAND (OC)
443-57	MC3003P		Quad 2-Input OR
443-61	MC4016P		Quad Bilateral Switch
443-62	MC4044		Phase Detector for PLL
443-65	7427		Triple 3-Input NOR
443-66	74192N		Up/Down Decade Counter
443-67	MC8601P		Retrig Monostable
443-70	74H103N		Dual JK Flip-Flop
443-71	74H00N		Quad 2-input NAND High Speed
443-72	7417N		Hex Buffer Driver
443-73	7416N		Hex Inverter Buffer
443-74	74452		
443-77	7438		Quad 2-Input NAND

443-79	95H0359	95H03	Trpl 2-Input OR/NOR (180MHz)
443-80	MC1035		Triple Diff Amp
443-81	95H02		Dual 4-Input OR/NOR (180MHz)
443-82	952859	9528	Dual D (160MHz)
443-83	95H2859	95H28	Dual D-Type Flip-Flop (180MHz)
443-84	MK5009		Mostek Oscillator Scaler chip
443-85	74157	9322	Quad 2-line to 1-line
443-86	9503		Trpl 2-Input OR/NOR (160 MHz)
443-87	74145N		BCD To Decimal Decoder
443-89	7409N		Quad 2-Input AND
443-90	74123		Dual Retriggerable Monostable
443-94	7483		4-bit full adder
443-95			600 MHz Decade Counter
443-98	9582		Triple Line Receiver ECL
443-99	TMS0101		TI Calculator Chip
443-601	MK5017AA		Mostek Clock Chip w/ Alarm
443-602	DD700	DM8880	7-Segment Decoder Driver
443-603	CD4011		Quad 2-Input NAND
443-604	CD4007AE		Dual Comp Pair + Inverter
443-606	CD4027		Dual JK Flip-Flop
443-607	CD4013	14013	Dual D Flip-Flop
443-612	74193		Binary Counter
443-614	TIL306		Counter/Decoder/Driver/LED
443-615	TIL308		Decoder/Driver/LED
443-616	Custom IC		TV Clock Display
443-621	TMS0119		TI Calculator Chip
443-622	74147		10-line to 4-line decoder
443-623	74154		4-line to 16-line decoder
443-624	MC1023		Dual 4-Input OR/NOR
443-625	74132N		Quad 2-Input NAND (SchmTrig)
443-626	ICL6013		DVM Chip
443-628	74196N		Presetable 4-Bit Binary Cntr

443-629	7490AN		Decade Counter
443-633	74160		Presetable Up/Down Cntr
443-634	TMS0116		BCD In/Out 4-Funct Calculator
443-635	DM8214	54/75153	Dual 4-Input (three-state)
443-636	MC10116		Triple Line Receiver ECL
443-637	MK5017BA		Clock w/ Calendar (not Alarm)
443-638	9310		Presetable Up/Down Cntr
443-640	7493AN		4-Bit Binary Counter
443-641	S1856		Clock Chip
443-647	CD4046		Phase Locked Loop
443-677	MC10211		ECL Dual 3-Input NOR
443-679	MC10131		ECL Dual D-Flop ECL
443-680	7495		Shift Register
443-683	MC10102		Quad 2-Input OR gate ECL
443-687	MK5017AA		Mostek Clock Chip w/ Alarm
443-690	UHP491		
443-691	9368		7-Seg Display Driver
443-692	MK50254		Mostek Clock Chip w/ Alarm
443-694	F9368DC		7-Segment Decoder Driver Latch
443-695	CD4001		Quad 2-Input NOR
443-697	74S64		4-2-3-2 And-OR-Invert
443-698	7486N		Quad 2-Input Exclusive OR
443-699	MM14511		Dual BCD Counter
443-701	CD4049	14049	Hex Inverting Buffer
443-702	F3817		Clock Chip
443-703	CD4001		Quad 2-Input NOR
443-704	CD4002		Dual 4-Input NOR

443-706	CD4071	14071	Quad 2-Input OR
443-707	CD4515	MC14515	4 to 16 Line Controller
443-708	CD4516	MC14516	Binary Up/Down Counter
443-709	74C93		4-Bit Binary Counter
443-710	MK50240		Top Octave Generator
443-711	74LS247		BCD-7 Seg OC
443-712	MC14025		Triple 3-Input NOR
443-713	MC14028		BCD To Decimal Decoder
443-714	11C01		Dual OR/NOR
443-715	11C70		Master/Slave D Flip-Flop
443-716	11C05		Div By 4 Prescaler 1100 MHz
443-717	74126N		Quad Buffer
443-719	74LS266		Quad 2-input Exclusive OR OC
443-720	CD40097		TriState Hex Buffer
443-721	2112-2		256 x 4 SRAM
443-722	MC8601P		Retrig Monostable
443-723	MC10216		Triple Line Receiver
443-724	MC10124		Quad 2-Input AND/NAND ECL
443-725	MC10125		Hex ECL to TTL Translator ECL
443-726	MC10138		Decade Counter ECL
443-727	96L02		Dual Retrig Monostable
443-728	74LS00		Quad 2-Input NAND
443-729	74LS13		Dual 4-Input NAND
443-730	74LS74		Dual D-Flop
443-731	74LS290		4-Bit BCD Ripple Counter
443-732	74LS30		Single 8-Input NAND
443-	74LS293		4-Bit Binary Ripple Counter

733				
443-735	MC14512			8-Channel Data Selector
443-736	MC14508			Dual 4-Bit Latch
443-737	MC14518			Dual BCD Counter
443-738	MC14556			Dual 1-4 Decoder
443-740	MC1648P			VCO for PLL
443-743	CD40192			Up/Down Counter
443-746	MC1648P			VCO for PLL
443-751	CD4081			Quad 2-Input AND
443-752	74LS175			Quad D-FF
443-753	74S240			Octal Buffer Tri-State
443-754	74LS240			Octal Buffer Tri-State
443-755	74LS04			Hex Inverter
443-757	74LS161			4-Bit Sync Binary Counter
443-760	CD4040			12-Bit Binary Ripple Counter
443-761	IM6402			UART
443-764	2114	4045	6614	1k x 4 SRAM
443-765	MC10105			Triple 2-3-2-Input OR/NOR ECL
443-778	CD4093	14093		Quad 2-Input NAND Schmidt Trig
443-779	74LS02			Quad 2-Input NOR
443-780	74LS08			Quad 2-Input AND
443-781	74LS75			Quad D-Flop
443-782	74LS155			Dual 1:4 Demux
443-783	MC14022			
443-784	CD4070			Quad 2-Input Exclusive OR
443-785	74C221			Dual Monostable Multivibrator
443-791	74LS244			Octal Bus Driver Tri-State
443-	74LS132			Quad 2-Input NAND

792			
443-793	4702		Baud Rate Generator
443-794	75188	1488	RS-232 Driver
443-795	75189	1489	RS-232 Receiver
443-796	DM8130		10-Bit Comparator
443-797	74LS10		Triple 3-Input NAND
443-798	74LS20		Dual 4-input NAND
443-799	74LS157		Quad 2 to 1 Multiplexer
443-800	74LS27		Triple 3-Input NOR
443-801	74LS196		Binary Counter/Latch
443-802	74LS257		Quad 2 to 1 line multiplexer
443-803	74273		Octal D-Flop
443-804	74LS259		8-Bit Addressable Latch
443-805	74LS273		Octal D-Flop
443-807	74LS42		BCD to Decimal Decoder
443-808	4N26		Opto Coupler
443-811	74LS125		Quad Buffer
443-812	RO-3-2513/CGR001		
443-813	74LS90		Decade Counter
443-815	74LS193		4-Bit Up/Down Counter
443-817	74LS192N		Up/Down Decade Counter
443-818	74LS05		Hex Inverter
443-819	8838		Quad Bus Driver
443-822	74LS139		Dual 1-To-4 Decoder
443-824	74LS241		Octal Bus Driver Tri-State
443-827	MC6800P		8-Bit Microprocessor
443-828	74LS73		Dual JK Flip-Flop
443-	74LS76		Dual JK Flip-Flop

829		
443-836	CD4174	Hex Latch
443-839	74LS243	Quad Bus Transceiver
443-840	MC6875	6800 Clock Generator
443-842	1406	
443-848	MM5316	4-Digit Non-Mux Clock
443-852	9LS259	8-Bit Addressable Latch
443-855	74LS283	Adder
443-856	2350	Floppy Disk Controller (?)
443-857	74LS367	Hex Buffer / Driver
443-858	7414	Hex Inverter
443-863	74LS374	Octal D-Flop
443-869	DS8629	National Div by 100 Prescaler
443-871	MC14514	4-Bit Latch/4-16 Line Decoder
443-874	8250	UART
443-875	74LS32	Quad 2-Input Or
443-877	74LS138	3-To-8 Line Decoder
443-879	74LS174	Hex D-Flop
443-881	Z-80	Microprocessor
443-884	74LS242	Quad Bus Transceiver Tri-State
443-885	74LS245	Octal Bus Transceiver
443-887	CD4023	Triple 3-Input NAND Buffered
443-891	74LS86	Quad 2-Input Exclusive OR
443-892	74LS166	8-Bit Shift Register
443-896	74S02	Quad 2-Input NOR
443-897	74S04	Hex Inverter
443-900	74S74	Dual D Flip-Flop

443-906	MC6845		CRT Controller
443-913	5740		Keyboard Controller
443-915	74S86		Quad 2-Input Exclusive OR
443-916	CD4538		Dual Monostable
443-917	CD4030AE		Quad Exclusive OR gate
443-919	74LS126		Quad Buffer Tri-State
443-920	74LS85		4-Bit Magnatude Comparator
443-921	74LS390		Dual BCD Counter
443-927	CD4059		Programmable Div by "N"
443-928	CD4008B		4-Bit Adder
443-929	14017		Divide by 10 "Ring Counter"
443-931	CD4543		7-Segment Decoder Latch Driver
443-932	MC14544		300 Baud Modem
443-933	5101	51L01	256 x 4 RAM
443-935	74S153		Dual 4-Input Multiplexer
443-936	7454		8-Input And-Or-Invert
443-937	SP8685B		512 MHz Divide By 10/11
443-938	ICM7216D		Frequency counter Chip
443-939	MC6808P	MC6802P	8-Bit Microprocessor w/ Clock
443-940	SP8647B		
443-942	74LS123		Dual Retrig Monostable
443-948	74LS112		Dual JK Flip-Flop
443-949	ADC0804		A/D Converter
443-950	CD4072		Dual 4-Input OR
443-951	74LS51		AND/OR Invert
443-952	8250		UART
443-953	3880	Z80A	8-Bit CPU

443-955	74LS153		Multiplexer
443-957	14519		4-bit AND/OR select
443-958	CD4060		14 Stage Ripple Carry Bin Cntr
443-967	7406N		Hex Inverter
443-969	74LS196		Presettable 4-Bit Binary Cntr
443-973	74LS393		Dual 4-Bit Binary Counter
443-987	MM5430		Frequency Counter Chip
443-992	CD4051		8 Channel Analog Mux
443-995	SC-01	SC-02 (?)	Votrax Speech Processor
443-996	TMS5100		LPC Speech Synthesizer
443-1008	74LS221		Dual Monostable
443-1014	MC68A21P	MC68B21P	8-Bit Dual Peripheral Adapter
443-1016	6116		2k x 8 Static RAM
443-1019	MC6850P		ASYNCR Interface Adapter
443-1020	7407N		Hex Buffer
443-1027	6116		2k x 8 Static RAM
443-1032	MK4116-26P		16k Dynamic RAM
443-1039	74LS365A		Hex Buffer / Driver
443-1055	MSM5832		uP Real-Time Clock (Oki)
443-1060	MC1488P		RS-232 Driver
443-1066	D8253C-2		
443-1080	74ALS00		Quad 2-input NAND
443-1088	AM26LS31PC		Quad Diff Line Driver
443-1096	74ALS244		Octal Buffer Tri-State
443-1099	SD4324		Fibre Optic Schmitt Detector
443-1109	HCPL2531		Opto-Coupler
443-	MC6809		16-Bit uP

1111		
443-1117	74LS374 (Selected)	Octal D-Flop
443-1118	MD14518	Dual BCD Decoder
443-1123	MM5451	LED Display Driver
443-1124	74HC393	Dual 4-Bit Binary Counter
443-1125	74C165	8-Bit Shift Reg
443-1138	6264	8k x 8 Static RAM
443-1139	MC146818P	CMOS Real-Time Clock
443-1145	CD40106	Hex Schmidt Trigger
443-1146	14568	PLL Phase Detector
443-1147	14526	PLL Programmable Divider
443-1149	D7201C	
443-1150	WD1943PD	
443-1151	14555	Dual 1 of 4 Decoder
443-1155	CD4069	Hex Inverter
443-1164	RC4200	Analog Multiplier
443-1175	74HC32	Quad 2-Input OR
443-1188	TL851CN	Polaroid Digital Ranging Cntrl
443-1189	ADC0831	8-Bit Serial I/O A/D Converter
443-1196	74ALS1034	Hex Buffer
443-1200	OKI M205	
443-1201	TMS5110A	LPC Speech Synthesizer
443-1202	MC14028	BCD To Decimal Decoder
443-1231	74ALS030	
443-1235	74ALS299	8-Bit Universal Shift Reg
443-1239	74ALS138	3-To-8 Line Decoder
443-1259	6522	VIA Dual 8-Bit Parallel Port
443-	6551	UART Controller

1260		
443-1261	WD1935	HDLC Controller
443-1263	2212	NOV-RAM
443-1290	74LS7225	
443-1307	74HC02N	Quad 2-Input NOR
443-1308	74HC04	Hex Inverter
443-1309	74HC74	Dual D Flip-Flop
443-1311	74HC138	3-To-8 Line Decoder
443-1313	74HC175N	Quad D-Flop
443-1315	74ALS05AN	Hex Inverter
443-1317	74HC27	Triple 3-Input NOR
443-1318	74HC125	Quad Buffer
443-1319	74HC139	Dual 1-To-4 Decoder
443-1321	74HC174N	Hex D-Flop
443-1322	74HC126N	Quad Buffer
443-1326	74HC257N	Quad 2-Input Mux
443-1327	74HC4078N	8-Input NOR
443-1328	74HC298N	Quad 2-Input Mux/DeMux
443-1329	74HC367N	Hex Tri-State Buffer
443-1330	74HC368N	Hex Tri-State Inverter
443-1331	74HC373	Octal D Latch
443-1332	74HC390N	Dual BCD Counter
443-1333	74HC652P	Octal Registered Transceiver
443-1335	74HC515N	
443-1338	82C53P-2	Prog Interval Timer
443-1344	54HC137	1 of 8 Decoder
443-1362	74HC377	Octal "D" Flop

443-1367	74HCT00			Quad 2-Input NAND
443-1382	74HC374			Octal D Flip-Flop
443-1383	74HC123			Dual Retrigger Monostable
443-1390	74HC365			Hex Buffer Line Driver
443-1391	74HC366			Hex Buffer Line Driver
443-1392	84C00-04			Z-80 Microprocessor CMOS
443-1393	84C30-04			Z-80 Counter/Timer CMOS
443-1394	84C42-04			Z-80 Dual Serial Port CMOS
443-1414	74F646N			Octal Transceiver Register
443-1422	6264			8k x 8 Static RAM
443-1553	6264	5864		8k x 8 Static RAM
443-1703	84C00-06			Z-80 Microprocessor CMOS
443-1704	84C30-06			Z-80 Counter/Timer CMOS
443-1705	84C42-06			Z-80 Dual Serial Port CMOS

Programmable Device

444-17	MCM6830A ROM			used in ET-3400
444-19	2316		2k x 8 ROM	used in H-17
444-23	3870 uP	MK14262N-5	New Stock Available	used in ID-4001/ID-2090
444-29	2316	8316	2k x 8 ROM	used in H-19
444-31	3870 uP			used in H-14
444-37	2316	8316	2k x 8 ROM	used in H-19
444-46	2716		2k x 8 EPROM	used in H-19
444-69	3870 uP	MK14623N-5		used in SA-5010
444-76				used in ET-3400
444-80	VM61006A		Speech ROM	used in EE-3403
444-108	D8741A			
444-109	P3041			
444-110				used in Hero-1 (ET-18)
444-141	D8741A			
444-161	MK3870/42			

444-198-1	MC68764		8k x 8 ROM	used in Hero-1 (ET-18)
444-199	MK3870/42			
444-200-1	3870 uP			used in GC-1000 WWV Clock
444-205-1	8748 uP			used in GD-1530
444-221-1	2732	ET-18-4 Utility ROM	4k x 8 ROM	used in ET-18 (Option)
444-226	14L8CNS		PAL	
444-227	12L6CN			
444-239-1	2732	ET-18-7 Auto Mode	4k x 8 ROM	used in ET-18 (Option)
444-240	3870 uP			used in AD-1308
444-249	PLA			used in ET-18-6
444-250		System ROM Remote		used in ET-18-3
444-254-2	MC68A364 ROM		16k x 8 ROM	used in RT-18
444-275	VM61006A		Speech ROM	(See 444-80)
444-283-2	MC68A364 ROM		16k x 8 ROM	used in RT-18
444-293-1	3870 uP			used in GC-1000 WWV Clock
444-295	PAL			used in RT-18
444-319-1	2764	ET-18-9 Hero1 BASIC	8k x 8 ROM	used in ET-18 (Option)
444-344-1				used in 4850 Digital Scope
444-349	2764		8k x 8 EPROM	used in HD-4040
444-350	2764		8k x 8 EPROM	used in HD-4040
444-351	2764		8k x 8 EPROM	used in HD-4040
444-352	2764		8k x 8 EPROM	used in HD-4040
444-353	74288		FEPROM	used in HD-4040
444-449	16R6ACN		PAL	
444-461	16R8BCN		PAL	
444-475	27C256		32k x 8 CMOS EPROM	used in ID-5001
444-852	27C64		8k x 8 CMOS EPROM	used in HC-1032

444-1010	27C256	32k x 8 CMOS EPROM	used in ID-5001
444-9006	TMS2708JL-45		1024 x 8 EPROM
444-9033	MC68764	8k x 8 ROM	used in RT-18
Buy-Sell			
643-95	HD61604		LCD Driver (ID-5001)

My appreciation to Milton Ferguson for contributing 57 Items to list from his purchase of N.O.S. Heathkit Inventory (02/14/2002)
Thanks!!!!

This cross reference is constantly being added to from any additional manuals that I see or acquire.
Please check it often to stay current.

If you would like to add an item to this list, send me a copy of the Parts Identification page of your manual and I will add the parts.